

DIGIMERGE

Product FAQ

FAQ No: FAQ-080811-04

Date: August 11, 2008

Product: DHU504R

Record On Demand on a DHU504R DVR

To Turn Continuous and Motion Record OFF

- Press **Setup**
- Select *Record Menu*
- Scroll down to *Continuous/Motion Setup*



- Press **Enter** once, then (▼) and schedule will be highlighted.
- Press **Enter** twice
- Press the **Right arrow** (►) to highlight all the boxes in the first row
- Press the **Down arrow** (▼) to highlight the all the boxes in the bottom channels

-Press **Enter** once, a box will pop-up
 -Scroll up to "NONE", press **Enter**. A checkmark will appear beside "NONE", and then press return.



-Press **Return** twice, a box will come up "Configuration has been changed. Do you want to save the configuration? OK or CANCEL"
 -Press **Enter** on "OK".
 -Press **Return** to go back to the main screen.


To Turn On ALARM Recording for On Demand Record

Turning ON Alarm Schedule

1. Press the **Setup** button on the front panel of the unit.
2. Select *Record Menu*, press **Enter**
3. Scroll down to *Alarm Setup*
4. Press **Enter** once, then press down button once (▼)
5. Press **Enter** twice and the first block on the Time Interval Bar will be highlighted in dark blue.
6. Press the **right arrow** (►) to scroll to the right until you reach the last block (24) and (▼) to select channels.
7. Press **Enter** once, All the boxes should change to a light blue colour.
8. Press **Return** three times and a box will prompt you "Configuration has been changed. Do you want to save the configuration? OK or CANCEL" Select OK
9. Press **Return** to go back to the main screen.

Setting up the Alarm Inputs

-Connect the wires to the back of the unit.
 -Press **Setup**
 -Select *System Setup*
 -Select *Event/Sensor*
 -Scroll down to *Alarm IN*





- Press **Enter** and scroll to the Alarm number you have selected
- Press **Enter** and using the Up and down arrows change the Operation from Disable to Enable.
- Press **Enter**
- Scroll right to Type. Select the Type N/O or N/C
- Press **Enter**
- Scroll down to Apply and press **Enter**
- Press **Return** four times to get out of the Alarm menu

Each camera should have a green box on the top right hand corner. When the Alarm is triggered it will turn to a red box with an **A** beside it.